

CR18K6E-PFV

HCFC, R-22, 60Hz, 1- Phase, 208/230 V
UL High Temp



Production Status:

Electrical Components

Internal Protector			
Part No:	071-0546-24	Usage Description	
<u>Vendor Part Number</u>		<u>Vendor Name</u>	
15HM1959		T.I.	

Stator					
Part No:	546-5081-66				
Resistance:	+/-7%	Start Wdg:	3.66	Run Wdg:	1.27

Potential Relays			
Part No:	040-0166-15	Usage Description	
<u>Vendor Part Number</u>		<u>Vendor Name</u>	
RVA3AG6D-917		ELECTRICA	

Start Capacitor			
Part No:	014-0061-16	Low MFD:	43.00
Type:	Start Capacitor	High MFD:	52.00
User Description:	LOW TORQUE	Volts:	330

Start Capacitor			
Part No:	014-0061-28	Low MFD:	145.00
Type:	Start Capacitor	High MFD:	175.00
User Description:	HIGH TORQUE	Volts:	250

Run Capacitor			
Part No:	014-0064-05	Low MFD:	25.00
Type:	Run Capacitor	High MFD:	0.00
User Description:		Volts:	370

john norton
06/11/2015

