# CF12K6E-PFV

HFC, R-404A, 60Hz, 1- Phase, 208/230 V
Low Temperature

Production Status: Available for sale to all U.S. customers. Please check with your local Emerson Climate Technologies Representative for international availability.

## Electrical Components

### Internal Protector

Part No: 071-0546-08 Usage Description

| Vendor Part Number | Vendor Name |
|---|---|
| 15HM1889 | T I |

### Stator

Part No: 546-5081-52

Resistance: +/-7% Start Wdg: 1.98 Run Wdg: 0.55

### Potential Relays

Part No: 040-0166-19 Usage Description

| Vendor Part Number | Vendor Name |
|---|---|
| RVA4AG6D-921 | ELECTRICA |

### Start Capacitor

| | | | |
|---|---|---|---|
| Part No: | 014-0006-13 | Low MFD: | 189.00 |
| Type: | Start Capacitor | High MFD: | 227.00 |
| User Description: | HIGH TORQUE | Volts: | 330 |

### Run Capacitor

| | | | |
|---|---|---|---|
| Part No: | 014-0064-14 | Low MFD: | 40.00 |
| Type: | Run Capacitor | High MFD: | 0.00 |
| User Description: | | Volts: | 440 |



Copyright © 2010 Emerson Climate Technologies, Inc. All rights reserved.